



## **2700HM**

### **2.7kVA "HIREMAX RANGE PORTABLE PETROL GENERATING SET (3000rpm)**

<b>OUTPUT:</b>	2.7kVA/2.2kW 50Hz, 115 volt cte, single phase.
<b>CONTROL BOX:</b>	Alternator top mounted control box comprising 1 x 16a BS4343 & 1 X 32A 115volt socket outlets, c/w miniature circuit breaker overload protection
<b>ENGINE:</b>	Honda GX160 re-coil start, single cylinder air cooled petrol engine with "oil alert" low oil level shutdown, fitted with fuel tank and exhaust silencer.
<b>ALTERNATOR:</b>	Markon Heavy duty brushless maintenance free, alternator, single bearing.
<b>FUEL TANK:</b>	3.6 litre fuel tank giving 3.6 hours operation at 75% load
<b>FRAME :</b>	1" heavy duty tubular steel wrap-around frame
<b>MOUNTS:</b>	Angled anti-vibration mounts.
<b>NOISE LEVEL:</b>	70dB (A) @ 7 metres. 95Lwa
<b>DIMENSIONS:</b>	L610mm x W420mm x H410mm
<b>WEIGHT:</b>	36kg (dry).

**May 2011**

